

NM100 Sound Level Calibrator

NoiseMeters Limited

www.noisemeters.com

Checking Sound Level Meter Performance

- » Class 2 Calibrator
- » Dual Level 94 and 114 dB
- » Frequency 1kHz
- » Fits 1/2" Microphones
- » Low Battery Indicator

The NM100 Sound Level Calibrator is used to check and adjust the performance of the Sound Level Meter. The calibrator emits a tone of accurate level and frequency. Before making measurements, the calibrator is placed over the microphone, switched on and the reading on the meter can be checked and adjusted.



Specifications

Standards	ANSI S1.4 and IEC 942 Class 2
Level	94 and 114 dB \pm 0.5 dB
Frequency	1 kHz \pm 4%
Battery	9V. 20 hours operation
Operating Temp	0 to 40°C, 32 to 140°F

NoiseMeters USA

3233 Coolidge Hwy,
Berkley, MI 48072, USA
Tel: 888 206 4377
Email: info@noisemeters.com

NoiseMeters Limited

West End, Muston
YO14 0ES, England
Tel UK: 0845 680 0312
Email: info@noisemeters.co.uk



Shown calibrating the NM102 Sound Level Meter